

Technical Data

Solid state class D powered bass amplifier, 19" rack mountable, 2 rackspaces high.

Inputs

- 1 Jack 1/4" A for basses with normal output level, 3 MΩ
- 1 Jack 1/4" B for basses with higher output, additional pre-damping control, 4.7 MΩ

Equalization

| | | |
|---------------------|--------|---------------------|
| Bass | +15 dB | 60 Hz, -15 dB 30 Hz |
| Low Mid | ±12 dB | 150 Hz / 240 Hz |
| Mid | ±12 dB | 100 Hz - 2 KHz |
| High Mid | ±12 dB | 750 Hz / 1.5 KHz |
| Treble | ±15 dB | 8 KHz |
| Bass-Cut adjustable | | 20 Hz – 80 Hz |

Outputs

| | |
|--------------------|--|
| 2 Speakers | Speakon, pin 1+ and 2+ signal hot, pin 1- and 2- signal cold |
| 1 Phones | Stereo-jack 1/4" |
| 1 Balanced DI Out | XLR, pin 1 ground, pin 2 signal+, pin 3 signal -, switchable level |
| 1 Tuner Out | Jack 1/4" |
| 1 Effect Loop Send | Jack 1/4" |

Effects

- 1 Parallel Loop, post eq, with mix feature (0-100%) and footswitch activation, also usable as MP3 input (stereo input 1/4" jack) with Return Gain control +/- 5 dB

Switches

- 1 Tune (cancels all outputs without Tuner Out)
- 1 Input A/B (activates Input A or B)
- 1 Bass Cut On
- 1 Eq On
- 1 Low Mid H/L
- 1 High Mid H/L
- 1 Drive On
- 1 Voice On
- 1 Effect On
- 1 Ground Lift
- 1 DI pre/post Eq
- 1 DI 0dB/-20dB
- 1 Loop Return mono / MP3 In stereo
- 1 Footswitch jack Tune
- 1 Footswitch jack Drive
- 1 Footswitch jack Effect
- 1 Power switch 900watts/600watts
- 1 Power On

Special Features

- Class A input stage
- LED Overdrive indicators for pre-amp
- LED indicators for all basic switches
- Built in A/B box with separate damping control for Input B
- Di-Out level switchable, 0 dB or -20 dB

| | |
|--------------------|--|
| Output Power: | 900 watts / 4 Ω, 450 watts / 8 Ω, switch OFF or 600 watts / 4 Ω, 300 watts / 8 Ω, switch ON (pushed) |
| Frequency Range: | 20 Hz to 20 KHz -1 dB |
| Power Requirement: | 200-260 V AC 5A slo, 100-130 V AC 8 A slo |
| Dimensions: | 320 x 88 x 260 mm (12.6 x 3.5 x 10.2") |
| Weight: | 4 kg (9 lbs) |